

Funktionsbeschreibung

Die SPATZ HDMI-4XO 1.3 Verteiler verteilt und verstärkt einen DVI/HDMI Ausgang eines DVD-Players, PCs oder Satellitenempfängers auf bis zu 4 Displays. Der Verteiler unterstützt Bandbreiten bis 2,25 Gbit/s und alle Deep Color Modi und HD Bitstream Audioformate. Das Gerät verfügt über 2 Modi für das EDID Handling. Wenn die LED leuchtet wird das EDID des zuletzt gelernten Displays am Ausgang 1 an die Quelle übermittelt. Um das EDID neu zu lernen, deaktivieren sie die LED durch einen kurzen Tastendruck und halten dann den TASTER 3s gedrückt bis die LED zu leuchten anfängt. Nun ist das EDID des Displays am OUTPUT 1 in den Speicher des Gerätes geladen worden. Sollte diese Variante Probleme bereiten, können Sie das interne EDID des Gerätes verwenden, das eine grosse Anzahl von gängigen PC und HDTV Auflösungen enthält. Das interne EDID simuliert einen Monitor mit RGB Farbraum, da diese Norm mit HDMI und DVI Displays kompatibel ist. In diesem Fall übermittelt der Verteiler ein internes von den angeschlossenen Displays unabhängiges EDID mit den gängigsten PC und HDMI Auflösungen. Die Geräte können bei UXGA bis zu 3 mal kaskadiert werden, um grössere Verteilsystem aufzubauen.

KEIN AUDIO ?

Sollte der Verteiler kein Audio mehr durchleiten, dann hat das Gerät von einem Display das kein HDMI Audio unterstützt, das EDID geladen und deaktiviert damit die Audioausgabe eines am Eingang angeschlossenen HDMI Ausgabegerätes. In diesem Fall das interne EDID verwenden oder ein Display mit integrierten Lautsprechern am OUTPUT 1 anschliessen und die Lernfunktion ausführen.

Technische Daten

Versorgung	DC 5V min. 500mA
Videoeingang	DVI oder HDMI (HDCP)
Videoausgang	DVI oder HDMI (HDCP)
Unterstützte Auflösungen	480i –1080p VGA-UXGA
unterstützte Frameraten	24-120 Hz
Grösse	102 x 100 x 30 mm

RS-232 Pin Out

3,5mm jack	SubD 9-pin
Tip	Pin 3
Ring	Pin 2
Ground	Pin 5

Port Setting 57600 BAUD, 8N1

Serial Commands

"HPB" ;Hot Plug Break
 "EON" ;Echo On
 "EOF" ;Echo Off
 "R" ;RESET
 "SWD" ;Software Download

Functional description

The SPATZ HDMI-4XO distributes and amplifies one DVI/HDMI output of a DVD-player, PC or satellite receiver up to 4 displays. The units supports bandwidths up to 2,25 Gbit/s ,all deep color modes and all HD audio formats in Bitstream. It has 2 modes how to handle the EDID forwarding. When the LED is lid up the unit uses the EDID which has been learned previously from a display that has been connected to OUTPUT 1. If you want to learn EDID data from a display then connect at OUTPUT 1, touch the button so the LED is off and then hold it for min. 3 s. When the LED has lid up you have successfully stored the EDID data to the internal memory. An alternative method is to use the preprogrammed EDID that is permanently stored in the unit holding almost all PC and HDTV resolutions available. The internal EDID simulates a monitor with RGB colorspace because that is compatible with HDMI and DVI monitors.+ To activate press the button so LED is off. This may solve problems with incorrect EDID forwarding resulting in no picture with some sources. Up to 3 units may be cascaded to form larger distribution systems at UXGA resolutions. If you want to use the unit with DVI equipment you can get appropriate adaptors or cables from us or any other suitable source.

NO AUDIO ?

In case the distribution amp is not passing audio it might be that the unit loaded EDID information from a display that is not supporting HDMI Audio. In this case you have to connect a HDMI Audio capable display (typical with integrated speakers) at Output 1 or use the unit in the "internal EDID" mode that activates all audio supported by HDMI 1.3.

Technical Data

Power supply voltage	DC 5V min. 500mA
Video input	DVI or HDMI (HDCP)
Video output	DVI or HDMI (HDCP)
supported resolutions	480i –1080p VGA-UXGA
supported framerates	24-120 Hz
Dimension	102 x 100 x 30 mm